

Step 5 Call Free



- Press the “#” sign on your UNIFONE Dial pad.
- The VoipStunt Call Menu should appear on your screen.

- Press the “*” sign on your UNIFONE Dial pad to erase or delete any number or data entry you wish to change.

1. Use the UNIFONE dial pad, to dial the destination number of the party you wish to call.
2. Then press “DIAL” key to initiate your call.
3. You can lift the hand set at any moment to speak with the party you are calling.
4. Place the hand set back to the cradle to re-dial a new number or simply to end call.



Please note that when you call a number (even if it's local) you should always dial :

Country code + area code + subscriber number
Example: 1-408-7483320

Questions/Comments: send e-mail to:
online@4broman.net

No	COUNTRY	CODE
1	ARGENTINA	54
2	AUSTRALIA	61
3	AUSTRIA	43
4	BELGIUM	32
5	CANADA (LANDLINE/MOBILE)	1
6	CHILE	56
7	CHINA (LANDLINE/MOBILE)	86
8	DENMARK	45
9	FINLAND	358
10	FRANCE	33
11	GERMANY	49
12	HONG KONG (LANDLINE/MOBILE)	852
13	HUNGARY	36
14	ICELAND	354
15	IRELAND	353
16	ITALY	39
17	JAPAN	81
18	LIECHTENSTEIN	423
19	LUMEMBOURG	252
20	MALAYSIA	60
21	MONACO	377
22	NETHERLANDS	31
23	NEW ZEALAND	64
24	NORWAY	47
25	PANAMA	507
26	PUERTO RICO	787
27	PORTUGAL	351
28	SINGAPORE (LANDLINE/MOBILE)	65
29	KOREA	82
30	SPAIN	34
31	SWEDEN	46
32	TAIWAN	886
33	UNITED KINGDOM	44
34	UNITED STATES LANDLINE/MOBILE)	1
35	THAILAND	66
36	RUSSIA	7
37	PERU	51



REVISION G

Congratulations! On your purchase of State-of-the-art BROMAN™ UNIFONE series 701G

Here 's what you need to get started:

Installation and set-up time: Approximately 15 minutes.

This 5-step guide is designed to help you install your UNIFONE USB Dialer to provide you UNLIMITED FREE outgoing calls on your laptop / desktop PC



UNIFONE USB Dialer-Rev G
Allows you to connect to the multi-VOIP networks. Embedded with built-in DSP chip for better quality of sound.



Broman Activation Card (NEW)

- Activation card required to input Card Number and Password



Installation CD-ROM

- UNIFONE 701g Dialer Software (version G)



Laptop / Desktop PC Requirements:
Windows operating system
Win 2000 and XP and latest OS
USB interface (USB Port)



Internet Service

- Broadband DSL or Cable
- Wi-Fi / Wireless ISP

Step 1 INSTALL Software



Load the Installation CD

- Remove CD from its casing
- Insert CD in Computer drive



PLEASE ENSURE YOUR PC / LAPTOP IS CONNECTED ONLINE ON THE INTERNET

1. BROMAN Start-up disk is auto-install when loaded to CD-ROM drive.
2. Please follow the instruction on the screen menu until the installation process has been completed.
3. After software installation , you can now go to step 2 (PLUG your device to USB port)

Step 2 PLUG your device



- Plug-in your UNIFONE USB Dialer to your Laptop/Desktop USB interface.



- Notice on the lower task bar: the RED icon changes to GREEN when you plug in the phone

Step 2 (continued)



- Once the “GREEN” icon has stabilized and does no longer change from RED to GREEN or vice versa, you can now lift the handset from the UNIFONE base.
- The BROMAN e-Tone screen menu will appear as shown below and inform “no services” **when you lift the handset**



Step 3 Service Activation

1. **Keep the handset lifted** as if you were planning to place a call for all the following steps.
2. **Scratch off the Password** in the Activation Card
3. **Enter the Card Number + Password** (no space) using the Phone Dial Pad keys
4. Hit the “Dial” Button on the Phone keypad.
5. **You will see** “Registration Completed” along with your Card Number+ Password as follows:



5. **You have now successfully activated** BROMAN Service for UNLIMITED & FREE Calls.
6. The BROMANTM e-Tone Server automatically identified your UNIFONE device on the network Server and signed you in using your 20-digit Subscriber Unit Number (see example above).
7. **Return the Handset to its Cradle**

Step 4 Test the Device

1. **Lift the Handset** as if you wanted to place a call
2. You should now see the **Expiration Date** of BRIO-MAN Service. A reminder will automatically appear one month prior to expiration



Also NOTE the following:



This message “The Client is logged on” should *also* appear on your BROMAN menu. **Your UNIFONE is now ready for use.** You can now call 37 global destinations using UNIFONE (Free & unlimited, *anytime, from anywhere within the network*).